捷波 EZ-远程更新 BIOS 说明

Jetway 提供分步骤指导,帮助客户只需点击几下鼠标即可轻轻松松更新其远程设备的 BIOS。根据应用程序设置,共有 3 个方案选择。

更新要求:

- 1. O/S: Win7, Win8.1, Win10, Win11
- 2. 软件:
 - Afuwinx64
 - Anydesk 或其它任一远程桌面应用程序 (仅限于方案 C)

<方案 A>:由现场技术人员更新现场设备

步骤 1: 从官网 https://www.jetwayipc.com 下载相关 BIOS_win 文件。

步骤 2: 打开下载文件夹单击"查看"选项卡,确认勾选"文件扩展名"选项框,并将 BIOS_win.zip 重命名为 BIOS_win.exe 执行程序文件。

↓ ↓ ↓ Download File Home Share	View					
Navigation Details pane	Extra large icons Small icons Extra large icons Extra large icons	Large icons	Medium icons	Sort By •	Group by * Add columns * Size all columns to fit	 ☐ Item check boxes ✓ File name extensions ☐ Hidden items
Panes		Layout		Ci	urrent view	Show/hide
\leftrightarrow \rightarrow \checkmark \uparrow \clubsuit > This	is PC → Downloads					
 ✓ ≱ Quick access ■ Desktop 	Name BIOS_win.zip	Date modified 10/24/2022 6:37 PM	Type Compressed (zipp	Size 9,822 KB		
👆 Downloads 🛛 🖈						

步骤 3: 如下图所示,右键单击 BIOS.exe 执行程序文件后选择"以管理员身份运行"。



步骤 4: 输入"Y"开始 BIOS 更新。务必保证更新过程不断电(等待 3 分钟)。更新完成后再重新启动电脑!

C:\windows\System32\cmd.exe	
Are you sure to flash the BIOS[Y/N]/y	
AMI Firmware Update Copyright (c) 1985-2022, Americ All rights reserved. Subject	Utility v5.15.03.0081 an Megatrends International LLC.
Reading flash - ME Data Size Checking - System Secure Flash - FFS Checksums - Check RomLayout Loading File To Verify Memory Erasing Main Block - Updating Main Block	Done Pass Enabled Pass Pass Done Done 0x00117000 (14%)

<方案 B>: 通过内联网更新设备 BIOS

步骤 1: 参考方案 A 步骤,从主机端下载 BIOS 档案并将档案重新命名为.exe 格式。

步骤 2: 运行远程桌面连接,通过 Intranet 远程连接客户端设备。



步骤 3: 将 BIOS 文件从主机端传输到客户端设备后,从客户端设备打开文件开始更新。打开"Downloads(下载)"文件夹,右键单击 BIOS.exe 程序并单击"以管理员身份运行",如下所示。



步骤 4: 输入"Y"开始 BIOS 更新。务必保证更新过程不断电(等待 3 分钟)。更新完成后再重新启动电脑!

C:\windows\System32\cmd.exe	
Are you sure to flash the BIOS[Y/N] y	
AMI Firmware Update	Utility v5.15.03.0081
Copyright (c) 1985-2022, Americ	an Megatrends International LLC.
All rights reserved. Subject	t to AMI licensing agreement.
Reading flash	Done
- ME Data Size Checking	Pass
- System Secure Flash	Enabled
- FFS Checksums	Pass
- Check RomLayout	Pass
Loading File To Verify Memory	Done
Erasing Main Block	Done
- Updating Main Block	0x00117000 (14%)

<方案 C>:通过互联网远程更新客户端设备

步骤 1: 参考方案 A 步骤,从主机端下载 BIOS 档案并将档案重新命名为.exe 格式。

<u>步骤 2:</u> 在主机端和客户端同事安装 Anydesk 应用程序后,在客户端运行 Anydesk 应用程序并将地址码(XXX-XXX)共享给主机端。

 Enter Remote Address 	No.		€ →
Your Add	dress 896 059	195 🗈 🛋 Invite	
News Favorites Recent Se	essions Discovered Invitat		000 000
News Favorites Recent Se	essions Discovered Invitat	ions	88 88
News Favorites Recent Se News What's new in AnyDesk 7.0?	ssions Discovered Invitat	Discovery	00 88
News Favorites Recent Set News	Install AnyDesk Install AnyDesk Install AnyDesk on this. device	Discovery Find other AnyDesk clients in your local network automatically.	88 88 9

<u>步骤 3:</u>在主机端键入从客户端获取的地址码有单击"→"链接客户端设备。

86085 Ke	ey in Address Code f	rom Client-device	
Your Add	Iress 20-45() 4 1 • • <u>* invite</u>	Click arr
News Favorites Recent Se	ssions Discovered Invita		88 11 1
What's new in	Juneal Analysis	Discovery	
What's new in AnyDesk 7.1? Check out the most interesting new features in this release	Install AnyDesk Install AnyDesk on this device	Discovery Find other AnyDesk clients in your local network automatically.	

步骤 4: 客户端设备将显示 Windows 安全警报,请单击"允许访问"以便主机连接并获得读/写权限。



步骤 5: 接着出现以下对话界面,点击"接受"允许对方连线。

		Chat	File Transfer
Y	Administrator (681832901)	Open Chat Log	
the second	desk.		
8 🖸			
Profile Default	~		
E	i 🔹 🗖		
۵	More		
	🗘 Accept		
Accept	Dismiss	M	

步骤 6: 出现下图界面表示主机端和客户端连线成功。



步骤 7: 如下图所示,接下来主机端可以按下绿框"上传(Update)"开始上传 BIOS 更新包。

♦ AnyDesk	Hos	t-Con	nuter	's Sore	on				
896059195	103	t con	iputer	3 JUIC		0 ¥ 🖻 Ö Ç) Ę 4	• • •	L
Administrator (681832901) This device	XB	7 Upload	∠ Download	θX	Administrato	r (896059195) Remote device	Ţ	F93H1ST5_WII 6.30 MiB Finished (Uploar	N.zip N
← ↑ ☆ ♡ C:\Users\Administrator\Do	winloads	×	↑ A 0 0	\Users\Administrator\D	ownloads	×			
Name Type	Size	Modified	Näme	∽ Type	Size	Modified			
T AnjOeskeze	3.63 Mil	2022/1/25 上午 01:3_	desition		282 8	2022/1/24 上午 06:4			
Frahrists_WWLap	630 MB	2022/1/24 上午 065-	F93H1ST5_WN.zip		6.30 MB	2022/1/24 上午 065			
G dabras	9510148	000/00 I T 013-							
Host-Con	npute	r		Client-o	device	е			

步骤 8: 如下图所示,点击主机端 🖳 图标连接客户端设备桌面。

♦ AnyDesk	Q			- 0	×
 896059195 	@ X 🖯	* 8 0 0 0 0	9 🖬 (Ð 🔍 🗸	. ≣
2 R					
2 🖸					

<u>步骤 9:</u> 打开"Downloads(下载)"文件夹,右键单击 BIOS.exe 程序并单击"以管理员身份运行",如下所示。

↓ ↓ ↓ File Home Shar	e View	Manage Application Tools	Dow	nloads	220
← → ~ ↑ ♥ > T	his PC → Do	wnloads		ٽ ~	Search Downloads
Ouick access	Name	^ Date mo	odified	Туре	Size
Desktop 🖌	BIOS	.exe 10/24/2	022 2	Open	
👆 Downloads 🚿				Run as adm	inistrator
🔮 Documents 🖈				Troubleshoo	ot compatibility
Pictures 💉				Pin to Start	
💻 This PC			1	Scan with W Share	/indows Defender
📄 Network				Give access	to

步骤 10: 输入"Y"开始 BIOS 更新。务必保证更新过程不断电(等待 3 分钟)。更新完成后再重新启动电脑!

C:\windows\System32\cmd.exe	
Are you sure to flash the BIOS[Y/N]?y	
AMI Firmware Update Copyright (c) 1985-2022, Americ All rights reserved. Subject	Utility v5.15.03.0081 an Megatrends International LLC.
Reading flash - ME Data Size Checking - System Secure Flash - FFS Checksums - Check RomLayout Loading File To Verify Memory Erasing Main Block Updating Main Block	Done Pass Enabled Pass Pass Done Done 0x00117000 (14%)